

MB720M2K-B

MB720MK-B V3



Mini-SAS HD SFF-8643 Connector



OCuLink SFF-8612 Connector

Scan the QR code for more product information

Copyright © ICY DOCK International. All Rights Reserved. 650308 VER 1.0




Cremax Europe GmbH  
Email: support@icydock.com  
Weidenweg 21H, 47059 Duisburg, Germany




Beyond Technologies UK Ltd  
Email: info@beyondtech.co.uk  
Unit B6, Halesfield 11, Telford, Shropshire, TF7 4PH, U.K.

1


Package Contents • Packungsinhalt • Contenu • Contenido del paquete • 包装について • 包装説明 • 包装说明




Device



User Manual



Drive ID Plugs



Thermal Pads  
x 4  
x 8



Key x 2



10 x M3\*2.5 Pan Head Screw for Device  
(2 x Screw for Spare Parts)


Note : Please use the included screws to secure the device

2

Device Information • Geräteinformationen • Informations dispositif • Información del dispositivo • 本体説明 • 機體説明 • 机体说明

▼ Front View


MB720M2K-B / MB720MK-B V3



- 1 2-segment Key Lock
- 2 Slot for Drive ID Plug
- 3 LED Indicator (Device Power : Solid Green ; Drive Access : Flashing Green )
- 5 M.2 SSD 22110/2280/2260/2242/2230 Lock Points

▼ Tray Inner View


MB720M2K-B / MB720MK-B V3



- 4 Adjustable M.2 Locker
- 6 Heat Sink Secure Points


▼ Rear View

MB720M2K-B



- 1 15 Pin Power
- 2 3 Pin Fan Header
- 3 Fan Switch
- 4 Mini-SAS HD Connector

MB720MK-B V3




- 5 OCuLink Connector

3

Installation Guide • Installationsanleitung • Guide d'Installation • Guía de instalación • 製品の組み込み手順について • 操作步驟 • 操作步驟


3-1



3-2




3-3




The metal heat sink needs to be removed before M.2 SSD installation. To remove, simply push the heat sink upward from the rear underside of the drive tray.

3-4




To prevent incorrect positioning of the M.2 SSD, align the gap on the connector of the M.2 SSD to the drive tray's slot divider. Then insert the M.2 SSD towards the connector slot.

3-5




With the M.2 SSD laying flat on the tray, slide the adjustable M.2 locker to secure the M.2 SSD.

3-6




Paste the thermal pad onto the heat sink cover after removing the protective film.

(Optional)



Remove the protective films and then paste the small piece thermal pads onto the lower component for a complete contact if there is a significant height difference between the components on the M.2 drive.

3-7




Place the removed heat sink cover back on.




Press down both sides of the heat sink cover to secure.

3-8



3-9




(Optional) Insert the drive ID into the slot, according to your preference.


4

Device Installation • Installation eines Gerätes • Installation du dispositif • Instalación del dispositivo • デバイス取付手順 • 装置安裝步驟 • 设备安装步骤

MB720M2K-B



MB720M2K-B / MB720MK-B V3



1. Use a small plier to external 5.25" bay cover and the Mini-SAS HD ports before connecting the cables.
2. Insert the device into external 5.25" bay and use the included M3\*2.5 screws to secure the device.
3. Connect the power & Mini-SAS HD / OCuLink cables to the device to complete installation.



ICY DOCK reserves the right to change product specifications, components, or accessories without prior notice. For the warranty information, please visit [www.icydock.com/warranty.php](http://www.icydock.com/warranty.php)